



Alutech Levigato handset programming

P2—RADIO CONTROL SETUP		
5	P2-F1—Recording the radio controls in the one-button control mode with function 'step-by-step' (SBS) into the memory	
5.1	Press and hold PR./◀ for about 5 secs to enter the programming mode	
5.2	Using OP./▲ and CL./▼ select program 'P2' on the menu	
5.3	Press ST./▶	
5.4	Using OP./▲ and CL./▼ select function 'F1' on the menu	
5.5	Press ST./▶	
5.6	'rc' is shown on the display, which means that the recording of remote controls in 'step-by-step' mode is expected	
5.7	Press the selected control button on the remote control three times	
5.8	The indicator will automatically show the number offered for a remote control in the drive memory (the number can be changed using buttons OP./▲ and CL./▼)	
5.9	Press ST./▶ to confirm; after that a dot will appear on the display	
In one second the automatic switch to the recording of the next remote control will take place. To exit the programming mode press PR./◀ or wait for 15 seconds		